AL-TR-1992-0154

AD-A260 934

DESIGN, FABRICATION, AND TESTING OF A THREE-DIMENSIONAL ACOUSTIC ORIENTATION INSTRUMENT (3-D AOI)--DRAWINGS, ENGINEERING, AND ASSOCIATED LISTS (CONCEPTUAL AND DEVELOPMENT DESIGN)

Dan D. Fulgham
Jeffrey Gabelmann

Southeastern Center for Electrical Engineering Education
1101 Massachusetts Avenue
St. Cloud, FL 34769

DTIC
ELECTE
FEB 1 7 1993
S   D
C

A R M S T R O N G   L A B O R A T O R Y

CREW SYSTEMS DIRECTORATE
2504 D Drive, Suite 1
Brooks Air Force Base, TX 78235-5104

December 1992

Final Technical Report for Period 1 May 1989 - 15 April 1991

93-02965

AIR FORCE MATERIEL COMMAND
BROOKS AIR FORCE BASE, TEXAS

NOTICES

This technical report is published as received and has not been edited by the technical editing staff of the Armstrong Laboratory.

When Government drawings, specifications, or other data are used for any purpose other than in connection with a definitely Government-related procurement, the United States Government incurs no responsibility or any obligation whatsoever. The fact that the Government may have formulated or in any way supplied the said drawings, specifications, or other data, is not to be regarded by implication, or otherwise in any manner construed, as licensing the holder, or any other person or corporation; or as conveying any rights or permission to manufacture, use, or sell any patented invention that may in any way be related thereto.

The Office of Public Affairs has reviewed this report, and it is releasable to the National Technical Information Service, where it will be available to the general public, including foreign nationals.

This report has been reviewed and is approved for publication.

KENT K. GILLINGHAM, M.D., Ph.D.   RONALD C. HILL, Lt Col, USAF, BSC
Project Scientist   Chief, Flight Motion Effects Branch

RICHARD L. MILLER, Ph.D.
Chief, Crew Technology Division

DTIC QUALITY INSPECTED 3

December 1992   Final - 1 May 1989 – 15 April 1991

Design, Fabrication, and Testing of a Three-Dimensional Acoustic Orientation
Instrument (3-D AOI)--Drawings, Engineering, and Associated Lists   C - F33615-87-D-0609
(Conceptual and Developmental Design)   (Task 0031)
                                                                             PE - 62202F
                                                                             PR - 7930
Dan D. Fulgham   TA - 20
Jeffrey Gabelmann   WU - 02

Southeastern Center for Electrical Engineering
   Education (SCEEE)   SwRI Project No. 12-3384
1101 Massachusetts Avenue   SCEEE-ARB/90-0031
St. Cloud, FL 34769

Armstrong Laboratory
Crew Systems Directorate
2504 D Drive, Suite 1
Brooks Air Force Base, TX 78235-5104   AL-TR-1992-0154

Armstrong Laboratory Technical Monitor: Dr. Kent K. Gillingham, (210) 536-3521

     Subcontractor (Southwest Research Institute) provides a description of the hardware assembled and software created to develop the 3-D AOI. A Macintosh IIx computer is the heart of the system, acting as a general controller and processor of data flowing from the Flight Information Package to the Audio Localization Cue Synthesizer, audio mixer, headphones, and data recording equipment. A National Instruments NB-DSP2300 digital signal processing board and NB-A2100 audio I/O board generate the audio signals, and National Instruments LabView software is used to control the auditory display. The majority of this report is a description of the 18 LabView software modules created to control the 3-D AOI display.

Acoustic orientation   Flight instrumentation   129
Auditory localization
Aural displays

Unclassified   Unclassified   Unclassified   UL

SYSTEM FUNCTIONAL BLOCKS

The AOI3 system performs the following basic tasks:

o   flight parameter data acquisition and storage,

o   flight parameter to acoustic parameter conversion (i.e., generation of audio cues),

o   user interface maintenance, and

o   presentation of audio cues for localization.

Figure 1 shows a block diagram overview of the AOI3 system. A MAC IIx is the heart of the system and acts as a central controller to perform the required system tasks. The following paragraphs describe how each task is implemented.

FLIGHT PARAMETER DATA ACQUISITION

The MAC IIx is connected to the flight instrument package (FIP) via the Macintosh internal serial printer port. The MAC periodically polls the FIP for the flight parameter information which is formatted and converted to acoustic parameter information by the MAC. This data can also be time tagged and archived on the MAC's hard or floppy drive for later analysis.

FLIGHT PARAMETER TO ACOUSTIC PARAMETER CONVERSION

A National Instruments NB-DSP2300 digital signal processing board, in conjunction with an NB-A2100 audio I/O board is used to generate the audio cues. These boards are compatible with the MAC Nu-bus architecture and are supported by the National Instruments instrumentation software system, LabView. The LabView package provides the low level driver routines required to control the digital signal processor (DSP) and audio boards. In addition, LabView allows for high level graphical type programming which makes the system easy to program, flexible, and expandable.

USER INTERFACE MAINTENANCE

The AOI3 software allows an operator to monitor the flight and acoustic conversion parameters during each flight test. The user has the ability to update specific mapping parameters, thresholds, or system gains simply by changing the program front panel constants. The software also provides a menu driven user interface to collect and save the flight test results to the MAC hard drive.

LOCALIZATION OF AUDIO CUES

The previous phase of the AOI program (AOI2) involved the development of a flight capable system which lateralized the audio cue across the pilot subject's head. The primary goal of the AOI3 program was to develop a flight capable system which can be used to localize the audio cue in three dimensional space. This localization is accomplished through the use of a system referred to as the Audio Localization Cue Synthesizer (ALCS) provided by a third party vendor. The ALCS accepts serial azimuth and elevation commands from a host and localizes an input audio signal to these coordinates.

FIGURE 1. AOI3 BLOCK DIAGRAM

A final item to note regarding the AOI3 system block diagram is the mixer block. This mixer allows the localized sound to be mixed with a lateralized sound. The mixer also allows the operator to quickly change the overall volume of the AOI3 signal.

SYSTEM HARDWARE

The following is a listing of the AOI3 system hardware:

- o   MAC IIx

- o   NB-DSP2300 DSP Board

- o   NB-A2100 Analog I\O Board

- o   NB-DMA2800 DMA Board

- o   Audio Mixer

- o   RS232 to RS422 Convertor Boxes

- o   ALCS and Headtracker Unit

- o   4 Track Tape Recorder

The system components are mounted in a standard 19" equipment rack which is mounted to the seat rails in the Queen Air. A 1 KVA power invertor is used to supply 115 VAC to the equipment in the rack. Figure 2 shows the wiring schematic for the system.

FIGURE 2. SYSTEM WIRING DIAGRAM

4

SOFTWARE MODULE DESCRIPTIONS

The following is a module by module listing of the AOI3 software. For the purposes of this document, a module is defined as a custom written section of code and thus no LabView Virtual Intruments (VIs) appear on the structure diagram nor are they specified as parent or child modules (refer to the LabView users manual for a complete description of the LabView VIs).

Each module description contains:

(1) a section of text which describes the module's function,

(2) a listing of the module's inputs and outputs with a brief explanation of each, and

(3) a list of the calling (parent) and called modules (child).

The text section is followed by a graphical print out of the module's icon, the front panel, and the LabView code. A structure diagram (Figure 3) has been included to quickly show the interrelationship of all the AOI3 modules.

FIGURE 3. AOI3 STRUCTURE DIAGRAM

6

7

MODULE DESCRIPTION

FUNCTION NAME

AS TO VAR FREQ BPS W/GAIN

FUNCTION DESCRIPTION

This module converts the airspeed flight parameter to a variable bandpass white noise generator acoustic cue. The center frequency of the bandpass filter is proportional to the aircraft's airspeed. Additionally the volume of the white noise acoustic cue is proportional to the airspeed.

FUNCTION INPUTS

AIRSPEED OFFSET: This user updated input can be used to correct for DC errors in the FIP airspeed reading.

FILTER ORDER: Order of the Butterworth bandpass filter.

LOW and HIGH CUT-OFF: These two inputs are used to set the width (in Hz) of the Butterworth bandpass filter.

FUNCTION OUTPUTS

AIRSPEED: Aircraft airspeed as reported by the FIP.

CENTER FREQ: Mapped acoustic cue white noise center frequency.

*AS ATTN VALUE*: Mapped acoustic cue white noise attenuation value.

PARENT FUNCTIONS

AUDIO OUTPUT MANAGER

CHILD FUNCTIONS

NONE

Connector Pane

AirSpeed
Center Freq.
Output Array

AS to Var Freq BPS w/gain

Front Panel

AS Attn Value
0.00

AirSpeed
0

Center Freq.
0

filtr ordr
2

low cut-off
600.00

high cut-off
1000.0

Output Array
0

Airspeed offset
0.00

Block Diagram

9

AS to Var Freq BPS w/gain
Thursday, April 11, 1991   12:31

10

3D SYSTEM MANAGER

MODULE DESCRIPTION

FUNCTION NAME

3D SYSTEM MANAGER

FUNCTION DESCRIPTION

The 3D system manager is the top level software module for the 3D system code. Upon start up, the system manager calls the software modules which initialize the AOI system peripheral hardware. These hardware initializations include the FIP and ALCS serial communications ports and the direct memory access (DMA), digital signal processor (DSP), and audio output boards. Next, the system manager initializes its data storage arrays and loads the pitch circle tone array from the hard drive into system random access memory (RAM). The final start up operation is the mapping of the flight parameter user inputs to acoustic parameter constants.

Upon completion of the initialization routines, the system manager calls the audio output manager. The audio output manager retains control of the system operation until the program is terminated by the user at which time control reverts back to the 3D system manager. The system manager then de-allocates DMA resources and terminates the program.

FUNCTION INPUTS

NAME OF PITCH CIRCLE ARRAY FILE TO PLAY: This input is entered by the user. It is the name of the pitch circle tone array file created using the *RECORD PITCH CIRCLE* LabView file.

Tmax: This input is entered by the user. It is the front panel value entered on the *GENERATE PITCH CIRCLE* LabView file front panel during the operation of the *RECORD PITCH CIRCLE* algorithm. Tmax is the number of elements in the pitch circle tone array. The Tmax entered here must be the same as that entered when the pitCh circle tone array was generated and stored.

PITCH CIRCLE ARRAY DATA TYPE SPECIFIER: This input should not be changed. It informs the system manager software of the pitch circle array type. This type specifier is used when accessing the pitch circle tone array from the hard disK.

FUNCTION OUTPUTS

ERROR CODES: These codes inform the user of an error condition encountered while accessing the pitch circle tone array from the hard disc. An error of zero indicates a successful operation. Refer to the LAbView users manual for a description of all other error codes.

PARENT FUNCTIONS

NONE

CHILD FUNCTIONS

INIT AUDIO BUFFERING
INIT FIP COM
*INIT ALCS*
MAP ACOUSTIC PARAMS(NEW)
AUDIO OUTPUT MANAGER

## Connector Pane

3-D
System
Manager

3-D Sys Mngr (VV Taper)

Front Panel

Name of Pitch Circle
Array File to Play

Tmax

Pitch Circ Chan0 (G=0.5)

100

Pitch Circle Array Data Type Specifier

0

0

Open Folder Error Code

0.00

Open File Error Code

0.00

Retrieve Data Error Code

0.00

Close DataLog File Error Code

0.00

13

Initialize Hardware

Initialize FIP serial port (Modem)

INIT
FIP
COM

Initialize Audio, DSP, and DMA task

Init audio settings

Left chan DMA   0

Do you wish to initialize the ALCS?

YES

NO

True

Init. ALCS

False

this read is required to initialize the FIP message length global

READ FIP

14

Initialize Global Variables and Data Arrays

Tmax

iS2 Tmax

OLD FLP DATA ARRAY

STX,SIO,CHKSUM-HI,CHKSUM-LO,ETX

Initialize the flight parameter to acoustic parameter mapping variables

flight params to acoustic params (new)

Build the global pitch circle array

Hard Disk:Lab View 2 Folder:aci.lib:pitch circ files

OPEN

STOP

EXIT

EXIT

Retrieve Data Error Code

STOP

READ

EXIT

Pitch Circle array

-1

Execute System Management Tasks

Close DataLog File Error Code

STOP

Block Diagram

De-allocate DMA resources

◄ 3 ▶

A2100 Brd No.

0

channel no

17

AUDIO OUT MNG
(ASW-RL tpr)

1.8

FUNCTION NAME

AUDIO OUT MNG (ASW-RL tpr)

FUNCTION DESCRIPTION

The main function of the audio output manager module is to control the generation of the acoustic cues. Specifically, the module calls sub modules which asynchronously poll the FIP, scale the received flight data, and convert the flight data to acoustic cues. The audio output manager also controls the logging of the flight parameter data to the hard disc.

FUNCTION INPUTS

RUN/STOP: Front panel control which interrupts the algorithm operation. The software will prompt the user to either continue operation or terminate the AOI program. If continued operation is selected, the software will ask the user if he wishes to log data to the hard disc. If the data logging option is selected, the software prompts the user for the logged file name.

DATA LOGGING TIME BASE(SECS): Sets the sample rate for the data logging operation.

FUNCTION OUTPUTS

CALCULATED ROLL AZIMUTH: The audio output manager calls a sub module called ROLL TO AZ X-FORM which converts the FIP bank angle parameter to an ALCS azimuth angle. This indicator displays the converted roll azimuth angle.

FIP ROLL: FIP bank angle flight parameter.

VERTICAL VELOCITY: FIP vertical velocity flight parameter.

AIRSPEED: FIP airspeed flight parameter.

PITCH ARRAY DEVIATION: Number of elements skipped in the pitch array acoustic cue. This value is mapped from the vertical velocity.

CENTER FREQ(airspeed): Center frequency of the airspeed white BPS noise acoustic cue. This value is mapped from the airspeed flight parameter.

ERROR MESSAGES: Associated with the manipulation of the data log file (refer to the LabView manual for specific error codes).

LOGGED DATA TYPE SPECIFIER: Specifies the type of data to be logged to the hard drive by the data logging algorithm.

PARENT FUNCTIONS

3D SYSTEM MANAGER

CHILD FUNCTIONS

FLIGHT DATA MANAGER
AS TO VARIABLE BPS NOISE (W/GAIN)
ROLL TO AZ X-FORM
W TO PITCH CIRC X-FORM (W/TAPER)
GEN REF TONE

Audio Out Mng (ASVV-RL tpr)
Thursday, April 11, 1991   12:30

Connector Pane

Run/Stop

Audio Out Mng (ASVV-RL tpr)

Front Panel

21

Audio Out Mng (ASVV-RL tpr)
Thursday, April 11, 1991   12:30

Run/Stop

CALCULATED ROLL
AZIMUTH

0.00

FIP Roll

0.00

VERTICAL
VELOCITY

0

AIR SPEED

0

PITCH ARRAY
DEVIATION

0

CENTER FREQ

0

Debug

0.00

New DataLog File Error

0

Log Data Error

0

Close DataLog File Error

0

Data Logging Time Base (secs)

0.50

Logged Data Type Specifier

type specifier for SCALED DATA array

type specifier for AS center freq

0

type specifier for pitch data no. of elements skipped

0

type specifier for L-chan atn

0.00

type specifier for R-chan atn

0.00

Block Diagram

22

Audio Out Mng (ASVV-RL tpr)
Thursday, April 11, 1991   12:30

116

1

+

AS to variable Rate s/min

UU to pica circle x-form s/cart

2

6

RM to A2 x-form

SEND ALCS Cmd

90

FIP Roll

S&L

set angle command

◄False►

◄False►

No Data is being logged to disc at this time

Audio Out Mng (ASVV-RL tpr)
Thursday, April 11, 1991   12:30

Initialize Data Logging to Disc Function

True

0

Would you like to
save this data on
the hard disc?

Yes

No

Prompt operator for data log file name

Enter the save file name

STOP

Log
Data

25

Audio Out Mng (ASVV-RL tpr)
Thursday, April 11, 1991 12:30

Audio Out Mng (ASVV-RL tpr)
Thursday, April 11, 1991   12:30

False

1

Do you Wish to Continue Executing
the AOI Program?

Yes

No

27

COMPARE NEW WITH
OLD DATA

FUNCTION NAME

COMPARE NEW WITH OLD DATA

FUNCTION DESCRIPTION

Compares most recently received FIP flight data with the previously received values. If a difference is detected, this module calls a sub module which scales and stores the appropriate flight parameters. This module then reports which values have been updated to the calling module.

FUNCTION INPUTS

NONE

FUNCTION OUTPUTS

NEW DATA: Flag is set true if new data has been received.

SCALED DATA ARRAY ELEMENTS THAT HAVE BEEN UPDATED: Element numbers of the flight data parameters that have been updated.

PARENT FUNCTIONS

FLIGHT DATA MANAGER

CHILD FUNCTIONS

SCALE NEW DATA

Compare New with Old Data
Thursday, April 11, 1991   12:32

Connector Pane

NEW DATA
SCALED DATA ARRAY elements that have been updated

Compare New with Old Data

Front Panel

NEW DATA

SCALED DATA ARRAY elements
that have been updated

0

DEBUG

0.00

32

Compare New with Old Data
Thursday, April 11, 1991   12:32

Block Diagram

This VI returns a value of true for NEW DATA if the SCALED DATA ARRAY is updated. Updated array element numbers are also returned

◄True►

If new data is different from old data update the old data array, scale the new data, and set new data flag.

OLD FIP DATA ARRAY

Scale New Data

NEW DATA

SCALED DATA ARRAY elements that have been updated

[I16]

DEBUG

NEW FIP DATA ARRAY

OLD FIP DATA ARRAY

Null Array

33

Compare New with Old Data
Thursday, April 11, 1991   12:32

◄ False ►

Data has not changed so
do nothing.

34

FLIGHT DATA MANAGER

FUNCTION NAME

FLIGHT DATA MANAGER

FUNCTION DESCRIPTION

This function calls sub modules which asynchronously poll the FIP for flight parameters and which scale and store the flight data.

FUNCTION INPUTS

NONE

FUNCTION OUTPUTS

FLIGHT DATA HAS BEEN UPDATED: The sub module *COMPARE NEW WITH OLD DATA* checks to see if the most recent flight data obtained from the FIP is different from the previously received data. If differences exist, the sub module scales and saves the appropriate parameters and reports that the data has been updated.

SCALED DATA ARRAY ELEMENTS THAT HAVE BEEN UPDATED: The sub module COMPARE NEW WITH OLD DATA reports the element numbers of the scaled data array which have been updated.

PARENT FUNCTIONS

AUDIO OUTPUT MANAGER

CHILD FUNCTIONS

*COMPARE NEW DATA WITH OLD DATA*
READ FIP

Flight Data Manager
Thursday, April 11, 1991   12:32

Connector Pane

Flight Data Has Been Updated
SCALED DATA ARRAY elements that have been updated

Flight Data Manager

Front Panel

**Flight Data Has
Been Updated**

SCALED DATA ARRAY elements
that have been updated

0

Block Diagram

37

Flight Data Manager
Thursday, April 11, 1991   12:32

Check to see if data has changed. If data has changed, report changes to system manager.

Flight Data Has Been Updated

SCALED DATA ARRAY elements that have been updated

TF

[116]

1

Read Serial Data From the FIP

0

READ FIP

38

FUNCTION NAME

GENERATE REFERENCE TONE

FUNCTION DESCRIPTION

Generates an audio reference tone that is mixed into the AOI output. This tone serves as an audible reference mark on the analog flight data recordings to locate the beginning and ending of each logged data set.

FUNCTION INPUTS

NUMBER OF TIMES TO PLAY TONE: Tone is played once to mark the beginning of a data set and twice to mark the end.

FUNCTION OUTPUTS

NONE

PARENT FUNCTIONS

AUDIO OUTPUT MANAGER

CHILD FUNCTIONS

NONE

Connector Pane

Number of Times to Play Tone —— [aenrate ref tone]

Generate Reference Tone

Front Panel

Tone Duration (msec)
◁▷ 500.00

Duration of Pause between Tones (msec)
◁▷ 250.00

Number of Times to Play Tone
◁▷ 2

Tone Frequency
◁▷ 440.00

Tone Amplitude
◁▷ 5000.0

Blk LD Error
0

41

Block Diagram

A2100 Slot

No Samples

Tone Array

Zeroed tone array

A2100 Chan No

Halt DMA while output array is zeroed

2

STOP

Number of Times to Play Tone

I32

42

this X zeroes the output array

3

0

Duration of Pause between Tones (msec)

2

ms

EXT

47

Generate Tone Array

INIT ALCS

50

FUNCTION NAME

INIT ALCS

FUNCTION DESCRIPTION

This module initializes the ALCS. Initialization includes:

1) initializing the serial port,
2) sending 3Space tracker set up command,
3) sending headphone mode command, and
4) bore-sighting the iso-tracker unit.

Please refer to the ALCS manual for a description of each of these commands and their related timing constraints.

FUNCTION INPUTS

NONE

FUNCTION OUTPUTS

NONE

PARENT FUNCTIONS

3D SYSTEM MANAGER

CHILD FUNCTIONS

SEND ALCS COMMAND

Init ALCS
Thursday, April 11, 1991   12:33

init.
ALCS

Connector Pane

init.
ALCS

Init ALCS

Front Panel

TIME WAITED (seconds)

0

Block Diagram

52

Init.
ALCS

◀ 3 ▶

Wait 20 seconds

TIME WAITED (seconds)

20

seconds

Init ALCS
Thursday, April 11, 1991   12:33

Initialize the serial Port

◄ 0 ►

INIT
ALC5
COM

5"

Init. ALCs

Init ALCS
Thursday, April 11, 1991   12:33

Select 3space isotracker by sending the
Local 3space Tracker command

SEND
ALCS
CMD

1

55

◄ 2 ►

Initialize the elapsed time counter

T F

Init ALCS
Thursday, April 11, 1991   12:33

Select Synthesizer/Headphone Mode

Init ALCS
Thursday, April 11, 1991   12:33

Pause before sending   next command

◀ 5 ▶

1000

5

Init.
ALCS

Bore-sight Headtracker (this turns on the sound in the headphones)

SEND
ALCS
CMD

4

INIT ALCS COM

60

FUNCTION NAME

INIT ALCS COM

FUNCTION DESCRIPTION

This module initializes the ALCS serial port.

FUNCTION INPUTS

BUFFER SIZE: Size of serial buffer

ALCS SERIAL PORT NUMBER: Modem (0) or printer (1) port.

BAUD RATE: Serial baud rate.

DATA BITS: Number of data bits.

STOP BITS: Number of stop bits.

PARITY: Odd, even, none.

FUNCTION OUTPUTS

NONE

PARENT FUNCTIONS

3D SYSTEM MANAGER

CHILD FUNCTIONS

NONE

Init ALCS Serial
Thursday, April 11, 1991   12:34

Connector Pane

INIT
ALES
COM

Init ALCS Serial

Front Panel

Buffer Size
64

Alcs Serial Port No.
Modem

Baud Rate
9600

Data Bits
8

Stop Bits
1

Parity
None

Init ALCS Serial
Thursday, April 11, 1991   12:34

Block Diagram

This Sub VI
Initializes the Serial
Port

◄ True ▶

An error has occured
during the ALCS serial
port initialization process.
Please check the "Init
ALCS Serial" sub VI to
verify that the serial
parameters are set
correctly (9600 baud, 8
data bits, 1 stop bit, no
parity)

STOP

If error code is
TRUE, report the error to
the user

Global Variable
for Port No.

Buffer Size
I32

Alcs Serial Port No.
I32

Baud Rate
I32

Data Bits
I32

Stop Bits
I32

Parity
I32

Init ALCS Serial
Thursday, April 11, 1991   12:34

◁ False ▷

INIT AUDIO
BUFFERING

65

FUNCTION NAME

INIT AUDIO BUFFERING

FUNCTION DESCRIPTION

This module performs the following functions:

1) sets the audio output channel number,
2) sets the audio board DAC sample rate,
3) allocates DMA resources, and
4) generates the white noise array (airspeed audio cue).

FUNCTION INPUTS

CHANNEL NUMBER: This input is passed from the calling function. The legal values are: 0 = left channel, 1 = right channel, and 2 = both channels. For AOI3 this input should be set to 0.

DURATION: This user selected input determines the update rate of the DMA process. This value multiplied by the audio board sample frequency must produce a DMA buffer size which is an even multiple of 4 (due to the way in which the DMA card allocates and updates its memory blocks).

SAMPLE FREQUENCY ARRAY: Sets DAC sample frequency selections. Do not change this input.

SAMPLE FREQUENCY: This user selected input determines the sampling frequency of the audio board 16 bit DAC.

GAIN: Amplitude multiplier for the airspeed audio cue white noise array. This array is generated during run time and saved in system RAM. A typical value for this input should be in the 200 to 300 count range.

ST. DEV: Standard deviation for the white noise array. Changing this value has little effect.

FUNCTION OUTPUTS

DMA BUFFER SIZE: Indicates calculated size of the DMA buffer. Must be a multiple of 4.

ERROR MESSAGES: DMA initialization error messages. Refer to LabView manual for a complete description.

PARENT FUNCTIONS

3D SYSTEM MANAGER

CHILD FUNCTIONS

SETUP DBUF
SETUP WAVEFORM GEN

Connector Pane

Channel No. ———— init audio buffring

Init Audio Buffering

Front Panel

Channel No.

0

0 = left
1 = right
2 = both

debug

2.00

DMA buffer size

1600.00

Duration X Sample frequency

Duration

0.050000

DMA channel
update interval

Sample Frequency Array

48000

Sample Freq Array

sampling frqy

16k

Audio board DAC
sample rate

1

Gain

300.00

The value is an amplitude multiplier
for the white noise array

St Dev

32.00

Standard deviation value for Gaussian
distributed random pattern

Error BWF Buffload
(L-chan)

0.00

Error
BWF Start
(L-chan)

0.00

Block Diagram

(-1)

DMA buffer size

SGL

number of noise samples

Initialize the DSP and A2100 Board

setup waveform gen

Channel No.

I16

white noise array

Gain

SGL

St. Dev.

SGL

Duration

SGL

White noise gen sample freq

Output Sample Rate

Sample Frequency Array

IS2

IS2

sampling frqy

65

Setup DMA Double Buffering

Error Buf_BufLoad
(L-chan)

EXT

Setup DBuf

AZ100 Slot No.

DSP/ AZ100 setup params

T F

1

Start Bandpass noise Waveform Generation Using the double Buffer

START

EXT

Error Buf_Start
(L-chan)

0

0

AZ100 Slot No.

DSP/ AZ100 setup params

T F

2

double no. samps for interleaved array

x

2

2

7/

MODULE DESCRIPTION

FUNCTION NAME

INIT FIP SERIAL

FUNCTION DESCRIPTION

This module initializes the FIP serial port.

FUNCTION INPUTS

BUFFER SIZE: Size of serial buffer.

FIP SERIAL PORT NUMBER: Modem (0) or printer (1) port.

BAUD RATE: Serial baud rate.

DATA BITS: Number of data bits.

STOP BITS: Number of stop bits.

PARITY: Odd, even, none.

FUNCTION OUTPUTS

NONE

PARENT FUNCTIONS

3D SYSTEM MANAGER

CHILD FUNCTIONS

NONE

Init FIP Serial
Thursday, April 11, 1991   12:33

Connector Pane

INIT
FIP
COM

Init FIP Serial

Front Panel

| Buffer Size |
| 64 |

| FIP Serial Port No. |
| Printer |

| Baud Rate |
| 9600 |

| Data Bits |
| 8 |

| Stop Bits |
| 1 |

| Parity |
| None |

73

Init FIP Serial
Thursday, April 11, 1991   12:33

Block Diagram

This Sub VI
Initializes the FIP
Serial Port

If error code is
TRUE,
report the error to
the user

◄ True ►

An error has occured
during the FIP serial port
initialization process.
Please check the "Init FIP
Serial" sub VI to verify
that the serial parameters
are set correctly (9600
baud, 8 data bits, 1 stop
bit, no parity)

STOP

Global Variable
for FIP Port
No.

Buffer Size
I16

FIP Serial Port No.
I32

Baud Rate
I32

Data Bits
I32

Stop Bits
I32

Parity
I32

SERIAL
PORT

74

INIT
FIP
COM

◄ False ►

75

76

MODULE DESCRIPTION

FUNCTION NAME

MAP ACOUSTIC PARAMS (NEW)

FUNCTION DESCRIPTION

The purpose of this module is to allow the user to quickly and easily update the AOI mapping variables. This module creates flight parameter to acoustic parameter mapping multipliers and stores these values in global memory. Changes must be made to these parameters prior to run time. Changes made while the program is running have no effect because this module is called only once during initialization.

FUNCTION INPUTS

MIN AIRSPEED VALUE: Sets the lowest airspeed for which the airspeed acoustic cue will respond. Airspeeds below this value will cause no change in the airspeed white noise center frequency.

MAX AIRSPEED VALUE: Sets the highest airspeed for which the airspeed acoustic cue will respond. Airspeeds above this value will cause no change in the airspeed white noise center frequency.

MIN NOISE PASS BAND CENTER POINT: Determines minimum airspeed acoustic cue passband center frequency. When airspeed is less than or equal to *MIN AIRSPEED VALUE* the airspeed acoustic cue center frequency is equal to this input value.

MAX NOISE PASS BAND CENTER POINT: Determines maximum airspeed acoustic cue passband center frequency. When airspeed is greater than or equal to MAX AIRSPEED VALUE the airspeed acoustic cue center frequency is equal to this input value.

MAX VV ROLL ANGLE: Sets the largest roll angle for which the airspeed and vertical velocity acoustic cues will be lateralized. Roll angles above this value will cause no change in the lateralization of the cues.

MAX AS ROLL ANGLE: This input is used for the AOI2 system only. It has no effect on the AOI3 system.

MIN AS LOW FREQ GAIN: This is the minimum gain value for the airspeed white noise acoustic cue. When airspeed is less than or equal to the *MIN AIRSPEED VALUE*, the airspeed cue is multiplied by the *MIN AS LOW FREQ GAIN*. The gain linearly approaches unity as the airspeed approaches the *MAX AIRSPEED VALUE*.

MIN VERTICAL VELOCITY: Must be set to zero for the AOI3 system.

MAX VERTICAL VELOCITY: Sets the largest vertical velocity for which the vertical velocity pitch circle acoustic cue will respond. Vertical velocities above this value will cause no change in the acoustic cue.

MAX PITCH CHANGE RATE: Determines the maximum number of tones to be skipped in the pitch circle tone array when vertical velocity is greater than or equal to *MAX VERTICAL VELOCITY*.

MAX TONE DURATION: Not used.

FUNCTION OUTPUTS

NONE

PARENT FUNCTIONS

SYSTEM MANAGER

CHILD FUNCTIONS

NONE

Connector Pane

map
acoustic
Params
(new)

Map Acoustic Params (new)

Front Panel

Min Airspeed Value 80
Max Airspeed Value 180

Max AS Roll Angle 3.00
Max VV Roll Angle 30.00

MinVert Vel 0
MaxVert Vel 2048

Min Noise Pass band Center Point 0
Max Noise Pass band Center Point 1000

min. AS low freq gain 0.10

Max Pitch Change Rate 20
Max Tone Duration (msec) 500

Block Diagram

77

81

MODULE DESCRIPTION

FUNCTION NAME

READ FIP

FUNCTION DESCRIPTION

This module polls the FIP for the flight parameters. The FIP looks for STX (decimal 02) to initiate the serial communications sequence. Upon receipt of STX the FIP sends SIO (decimal 01) then 18 data bytes (9 two-byte flight parameters) then two check-sum bytes then ETX (decimal 03). The READ FIP module calculates the check-sum and if it is valid concatenates the data bytes and stores the results.

FUNCTION INPUTS

FIP MESSAGE LENGTH: Number of bytes in the FIP serial message string.

SERIAL TIME OUT VALUE: Number of system clock ticks (one tick equals 16.7ms) the algorithm waits for an FIP message after sending STX. Once this limit is exceeded the algorithm reports an error and returns control to the calling module.

FUNCTION OUTPUTS

NUMBER OF BYTES IN THE SERIAL INPUT BUFFER: Number of bytes received from the FIP in the serial message string.

FIP SERIAL MESSAGE RECEIVE BUFFER: Contents of serial receive buffer. These are raw concatenated values.

FIP NEW DATA ARRAY: Concatenated FIP serial values.

PARENT FUNCTIONS

FLIGHT DATA MANAGER

CHILD FUNCTIONS

NONE

Read FIP (new)
Thursday, April 11, 1991   12:32

Connector Pane

```
READ
FIP
```

Read FIP (new)

Front Panel

READ
FIP

Read FIP (new)

Front Panel

Number of bytes in serial input buffer

22

Serial Read Error Message

A serial timeout error has occured

FIP Message Length (bytes)

22

Serial Time-out Value (system
clk ticks - one tick = 16.7ms)

17

FIP Serial Message Receive Buffer

0

0

FIP New
Dat. Array

0

AS	AA	VV	HDEV	ROLL	PT	ALTDEV	ALT	READ
2420	0	4095	277	2153	2012	12768	12565	260

Block Diagram

Serial Read Error Message

Checksum is OK so convert values to 2 byte integers

hi-byte
lo-byte

save data-packet in new data global array

NEW FIP DATA ARRAY

FIP New Data Array
[116]

check sum failed flag

55

True

True

False

A serial timeout error has occured

A serial checksum error has occurred

Flush the input buffer

Send STX to FIP and initialize the time-out counter and time-out flag

True

Error during FIP serial port write: Port No. out of range

True

Error during FIP serial port write: Port has not been initialized

=

=

-1

-28

False

False

2

2

Number of bytes in serial input buffer

True

FIP Message Length (bytes)

Serial Time-out Value (system clk ticks - one tick = 16.7ms)

False

A serial timeout error has occured reset the timeout flag

Read the FIP data packet from the serial buffer

◀ 3 ▶

◀False▶

Read string from input buffer and
convert to an array of unsigned bytes

[U8]

FIP Serial Message Receive Buffer

[U8]

◀True▶

Time-out has occured so build
a dummy array

0

Calculate the checksum on the data packet

91

True

Time-out has occurred so do nothing

ROLL TO AZ X-FORM

MODULE DESCRIPTION

FUNCTION NAME

ROLL TO AZ X-FORM

FUNCTION DESCRIPTION

Converts the aircraft bank angle to an ALCS azimuth angle. Refer to the ALCS manual for a complete description of the ALCS azimuth angle.

FUNCTION INPUTS

NONE

FUNCTION OUTPUTS

FIP ROLL: Aircraft bank angle as reported by the ALCS.

CALCULATED ROLL AZIMUTH: Calculated ALCS azimuth angle.

PARENT FUNCTIONS

AUDIO OUTPUT MANAGER

CHILD FUNCTIONS

NONE

Calculated Roll Azimuth

FIP Roll

Roll to AZ X-form

Calculated Roll
Azimuth
0.00

FIP Roll
0.00

Calculated Roll
Azimuth
SGL

True
360

FIP Roll
SGL

False
90.

Max
VV
Roll
Angle

Scaled
data
array

4

1.

Roll Element Number

SEND ALCS COMMAND

97

MODULE DESCRIPTION

FUNCTION NAME

SEND ALCS COMMAND

FUNCTION DESCRIPTION

Sends the indicated *ALCS COMMAND* via the serial port selected by INIT ALCS COM. This module includes a user configurable command array which pairs command numbers with the appropriate command serial message string. This array can be updated as new ALCS commands are added by the vendor.

FUNCTION INPUTS

AZIMUTH ANGLE: Angle between 0 and 359 degrees which locates an audio cue in the horizontal plane. Zero azimuth is defined as straight ahead with azimuth angle increasing in the clockwise direction.

ELEVATION ANGLE: Angle between 0 and 180 degrees which locates an audio cue in the vertical plane. Zero elevation is defined as straight up with 180 degrees of elevation being straight down.

ALCS COMMAND ARRAY ELEMENT NUMBER: The index number of the desired ALCS command message string. The command/index pairing are as follows:

0	Synthesizer/Headphone Mode
1	Local 3-Space Tracker
2	Free-Field Mode
3	System Reset
4	Zero Queue
5	Request Angle
6	Set Angle
7	Re-transmit Response

For a complete description of these commands refer to the ALCS users manual.

FUNCTION OUTPUTS

NONE

PARENT FUNCTIONS

INIT ALCS COMM
AUDIO OUTPUT MANAGER

CHILD FUNCTIONS

NONE

Send ALCS Command
Thursday, April 11, 1991   12:34

Connector Pane

Azimuth Angle

ALCS COMMAND array element number

Elevation Angle

Send ALCS Command

Front Panel

Send ALCS Command
Thursday, April 11, 1991   12:34

ALCS COMMAND
array element
number

6

ALCS COMMAND array

Set Angle

6

7   65   0

Azimuth Angle

0

Elevation Angle

0

Transmit Buffer

0

Block Diagram

Send ALCS Command
Thursday, April 11, 1991   12:34

Extract desired ALCS command from the command array menu. If the BYTE COUNT byte is 7,
add the azimuth and elevation bytes to the command. If the azimuth angle is greater than
255, it must be broken into 2 bytes.

ALCS COMMAND
array

ALCS
COMMAND
array
element
number

101

Send ALCS Command
Thursday, April 11, 1991   12:34

Send ALCS Command
Thursday, April 11, 1991   12:34

5

6

103

Send ALCS Command
Thursday, April 11, 1991   12:34

109

Send ALCS Command
Thursday, April 11, 1991   12:34

Calculate the checksum for
the serial message

Transmit Buffer

[u8]

Checksum is calculated by doing a
bit-wise XOR on all of the ALCS
command array elements

Initialize shift
reg. to zero

0

Send ALCS Command
Thursday, April 11, 1991   12:34

Transmit command message to the ALCS

106

SCALE NEW DATA

107

FUNCTION NAME

SCALE NEW DATA

FUNCTION DESCRIPTION

Scales the raw 12 bit A to D convertor data received from the FIP to the appropriate flight parameter data. Scaling values can be updated by the user on the front panel prior to run time.

FUNCTION INPUTS

ARRAY ELEMENT NUMBER: New FIP *DATA ARRAY* element number. This is the element number of the value to be scaled.

ARRAY ELEMENT VALUE: This is the actual value to be scaled.

FUNCTION OUTPUTS

NONE

PARENT FUNCTIONS

COMPARE NEW DATA WITH OLD DATA

CHILD FUNCTIONS

NONE

Connector Pane

Array Element Number ——— Scale
Array Element Value ——— New
Data

Scale New Data

Front Panel

SCALING VALUE ARRAY

◁▷ 3

HEADING DEV.

◁▷ 1.000

Array Element Number ◀▶ 0

Array Element Value ◀▶ 0

AS

AA

VV

HDEV

ROLL

PT

ALTDEV

ALT

READ

SCALED DATA ◀▶ 0

Block Diagram

SCALED DATA

[EXT]

False

Roll/Pitch data must be offset prior to scaling

Roll: left bank gives negative values
Pitch: nose down gives neg. values

2048

Scaling Value

Array Element Value

SCALING VALUE ARRAY

roll element

4

5

pitch element

Array Element Number

True

MULTIPLY NEW DATA BY SCALING VALUE AND SAVE IN THE SCALED DATA GLOBAL ARRAY

Scaling Value

111

112

MODULE DESCRIPTION

FUNCTION NAME

SETUP DBUF

FUNCTION DESCRIPTION

Initializes a DMA buffer for waveform generation. Sets rate at which the waveform buffer will be output and enables the block update DMA mode.

FUNCTION INPUTS

BOARD NUMBER: DMA board slot number.

NUMBER OF POINTS: Number of data points in waveform data, (i.e. the DMA buffer size).

SAMPLE RATE: Element number of desired sample rate (refer to *INIT AUDIO BUFFERING* module description).

CHANNEL NUMBER: Analog output channel number.

FUNCTION OUTPUTS

ERROR MESSAGE: Error code returned from buff load process. Refer to LabView manual for complete description.

PARENT FUNCTIONS

INIT AUDIO BUFFERING

CHILD FUNCTIONS

NONE

Connector Pane

BOARD NUMBER ——
Number of Pts ——
Sampling Rate ——
Channel No. ——

```
┌─────────┐── error/bufId
│  Setup  │
│  DBuf   │
└─────────┘
```

Setup Double Buffering

Front Panel

```
┌──────────────────────────────────────┐
│                           error/bufId │
│                          ┌──────────┐ │
│  ◁▷ 5                     │   0.00   │ │
│  BOARD NUMBER            └──────────┘ │
│                                        │
│  Number of Pts                         │
│  ◁▷ 1200                               │
│                                        │
│  Sampling Rate                         │
│  ◁▷ 5                                  │
│                                        │
│  Channel No.                           │
│  ◁▷ 0                                  │
└──────────────────────────────────────┘
```

Block Diagram

BOARD NUMBER

Number of Pts

Cycles (-1 continuous)

Sampling Rate

error/bufld

EXT

115

SETUP WAVEFORM
GENERATION

116

MODULE DESCRIPTION

FUNCTION NAME

SETUP WAVEFORM GENERATION

FUNCTION DESCRIPTION

This module initializes the A2100 Audio output board and the DSP2100 DSP board. Initialization parameters include slot numbers, sample rates, and input/output coupling. All of the initialization parameters are stored in a global variable for subsequent access from other modules.

FUNCTION INPUTS

A2100 SLOT: Slot number of audio output board.

DSP2300 SLOT: Slot number of DSP board.

INPUT SAMPLE RATE: Element number of desired input sample rate (refer to LabView users manual for details).

INPUT COUPLING: A2100 input coupling (AC, DC, or Ground).

A/D SERIAL LINK: Sets serial line connection between the A2100 and the DSP2300 boards.

D/A SERIAL LINK: Sets serial line connection between the A2100 and the DSP2300 boards.

GROUP SELECT: Set to 0.

INPUT SETUP: A2100 input link action (connect, disconnect, no action).

OUTPUT SETUP: A2100 output link action.

DMA BUFFER SIZE: Passed from calling function.

*A2100 CHANNEL NUMBER*: Passed from calling function.

FUNCTION OUTPUTS

NONE

PARENT FUNCTIONS

INIT AUDIO BUFFERING

CHILD FUNCTIONS

NONE

Connector Pane

```
D/A Serial Link
Output Sampling Rate
Output Setup
Input Setup
DSP2300 Slot

A2100 Slot
Input Sampling Rate
A/D Serial Link
DMA Buffer Size

Input Coupling
Group Select
A2100 Channel No.
```

Setup Waveform Generation

Front Panel

A2100 Slot
5

DSP2300 Slot
6

1 - 48 KHz

Output Sampling Rate
5

D/A Serial Link
0
(0, 2)

Output Setup
CONNECT
DISCONNECT —
NO ACTION —

Input Sampling Rate
5

Input Coupling
AC

Sampling Rates:
1 - 48 KHz
2 - 44.1 KHz
3 - 32 KHz
4 - 24 KHz
5 - 22.05 KHz
6 - 16 KHz

DMA Buffer Size
0

A2100 Channel No.
0

A/D Serial Link
1
(1, 3)

Group Select
0
(A2100 - 0 only)

Input Setup
CONNECT
DISCONNECT —
NO ACTION —

Block Diagram

117

CSCode 194

DSP/
A2100
setup
params

DSP2300 Slot

function code 704

error code 0

Input Sampling Rate

Input Coupling

A/D Serial Link

Group Select

Input Setup

Output Sampling Rate

D/A Serial Link

Output Setup

DMA Buffer Size

A2100 Channel No.

NB-A2100

A2100 Slot

False False True STOP

There is an error in the "SetUp A2100" module:

There is not a NB-A2100 in the indicated slot.

Continue

Stop

W TO PC X-FORM
W/TAPER

123

MODULE DESCRIPTION

FUNCTION NAME

VV TO PC X-FORM W/TAPER

FUNCTION DESCRIPTION

This module converts the vertical velocity flight parameter to a pitch circle audio cue. The array of tones used to generate the pitch circle is pre-recorded and stored on the hard drive. The *AOI SYSTEM MANAGER* module accesses the tone array from the hard drive and saves it in global memory during run time. This module skips elements in the tone array based on the mapped value of the vertical velocity flight parameter, thus giving the illusion of the pitch circle speeding up for higher values of vertical velocity.

FUNCTION INPUTS

PITCH CIRCLE ARRAY ELEMENT TO BE PLAYED: Array of tones to be played from the pitch circle tone array (the tone array is an array of arrays).

FUNCTION OUTPUTS

VERTICAL VELOCITY: Vertical velocity flight parameter obtained from the FIP.

PITCH ARRAY DEVIATION: Number of elements to skip in the pitch circle tone array.

## PARENT FUNCTIONS

AUDIO OUTPUT MANAGER

CHILD FUNCTIONS

NONE

VV to PC X-form w/taper
Thursday, April 11, 1991   12:31

Connector Pane

Pitch Circle Array Element to be played
vertical velocity
pitch array deviation

VV to PC X-form w/taper

Front Panel

Pitch Circle Array Element to be played

0

vertical velocity

0

pitch array deviation

0

Array Index (I)

0

Tmax

0.00

125

Block Diagram

VV to PC X-form w/taper
Thursday, April 11, 1991   12:31

VV is not above the threshold so output an array of zeroes

◄ False ▶

Max VV

I16

W element no.

scaled data array

4096 = 2048 Rvmin
2048 = 0 Rvmin
0 = -2048 Rvmin

2048.

Minimum VV

pitch array deviation

I8

Pitch Circle Arr
Element to be ple

[I16]

I18

DSP/
A2100
setup
params

127